

FEATURES + BENEFITS

4in1 | Gasoline Generator - Pressure Washer - Air Compressor - Battery Charger

- Multi-function in AC generator output, pressure washer, air compressor, DC battery charger.
- 2. Power output 6.0KW continuous, 7.5KW peak.
- The powerful 175Bar high-pressure Washer offers great performance and durability with a long-lasting **induction motor** and a **crankshaft pump**.
- 4. 275L/MIN air compressor.
- 5. DC12V/8.3A output for battery charge.
- 6. Genuine HONDA GX390 13HP air-cooled engine with electric/recoil starter.
- 7. 35L fuel tank provides up to 16 hours of operation on a single fill.
- 8. Built-in circuit breakers protect your equipment.
- Wheelbarrow-style running gear for easy maneuverability.
- 10. Patented











POWERED by **KOHLER**®

Email: sales@emaxpowers.com

www.emaxpowers.com





GRSOLINE GENERATOR





PRESSURE WASHER







BATTERY CHARGER





POWERED by HONDA KOHLER®

Email: sales@emaxpowers.com

www.emaxpowers.com

SPECIFICATIONS

	MODEL Rated voltage (V)	TT-4IN1	
Generator		AC230/240	AC120/240
	Frequency (Hz)	50	60
	Rated output (KW)	5	6
	Peak output (KW)	6	7.5
Battery Charger	DC output	12V/8.3A	
High Pressure	Electric motor size (KW)	2.2	3
Washer	Rated pressure	110Bar/1600PSI	130Bar/1850PS
	Max pressure	160Bar/2300PSI	175Bar/2500PS
	Rated flow (L/min)	7.4	9.5
Air Compressor	Electric motor size (KW)	1.3	1.6
	Air delivery (L/min)	215	275
	Working pressure (BAR)	8	
	Air tank (L)	18	
Gasoline	POWER (HP)	13	
Engine	Cooling system	Air cooling	
	Air valve	OHV	
	Fuel tank (L)	35	
	Ignition system	CID	
	Start mode	Electric, recoil	
Complete	L x W x H (mm)	860 x 760 x 1030	
Machine	Weight (kg)	160	